



ISSUED BY SERVICE DIVISION, HIS MASTER'S VOICE (N.Z.) LTD., G.P.O. BOX 108, WELLINGTON

## PERSONAL PORTABLE

**FOUR VALVE BATTERY OPERATED  
MODEL 484P.**

### VALVE COMPLEMENT

		Marconi.	R.C.A.	Philips
Osc.-Mixer	V1	X17	1R5	DK91
Amplifier	V2	W17	1T4	DF91
Det. A.V.C. Amp	V3	ZD17	1S5	DAF91
Output	V4	N17	3S4	DL92

### FREQUENCY RANGE

Broadcast: 550-1500Kcs.  
IF. Freq.: 455Kcs.

## BATTERIES

H.T. 67.5 volts Type 467  
L.T. 1.5 " " 950

The life of the batteries on normal (Intermittent) usage should be approximately H.T. 60 hours, L.T. 5 hours. If continuous service is required for periods of one hour or more it is recommended that two or more type 950 Batteries be used in rotation. This will allow the cells to recuperate.

### To Remove Chassis:




Remove the 3 screws positioned as follows:

1. Under 950 battery.
  2. Between Tuning Condenser and Volume Control.
  3. Under 462 Batteries.
- Then lift off outer cover.

Then lift off outer cover.

## PHYSICAL SPECIFICATIONS


Height 3in. Width 3½in. Length 9in.  
Weight: 4lb. 8oz. (including Batteries).



DRAWN BY	6976
CHECKED BY	WHW
DATE	1-9-48

made by Plessey

484P



## Personal Portable

**FOUR VALVE BATTERY OPERATED**

**I**N the field of Portable Radios the H.M.V. Portable has no equal. Housed in a cabinet of moulded "Perspex" and leather covered steel this Radio will stand up to all the rigours of hard work that Portable Receivers are subjected to. The special switching (built into the lid) acts as a safety device to protect the life of the batteries. When the lid is closed the Radio circuit is SWITCHED OFF automatically. Simplicity of operation and low running costs are big features in this Personal Radio.

Model 484P.

1948